



**Specifications LED Bulkhead Black  
12W 1200lm - 830 Warm White | IP54 -  
Light Sensor**

[View Product](#)

## General Information

|                          |                                                          |
|--------------------------|----------------------------------------------------------|
| SKU                      | 252443                                                   |
| EAN                      | 8719157056649                                            |
| Brand                    | Non-branded                                              |
| Manufacturer Name        | LED BULKHEAD   JULIET   12W   MET SENSOR   ZWART   3000K |
| Any Lamp all-in warranty | 5 Years                                                  |
| Average Lifetime (h)     | 50000                                                    |

## Technical Information

|                             |                 |
|-----------------------------|-----------------|
| Technology                  | LED Integrated  |
| Wattage                     | 12              |
| Voltage (V)                 | 220-240         |
| Dimmable                    | Not Dimmable    |
| Colour Code                 | 830 Warm White  |
| Colour temperature (Kelvin) | 3000 Warm White |
| Colour Rendering (Ra)       | 80-89           |
| Colour of Light             | White           |
| Light colour options        | Single Color    |
| Luminous Flux (Lumen)       | 1200            |
| Luminous Efficacy (lm/W)    | 80              |
| Optical Cover               | Plastic         |

Power factor >0.90

Product Type Category LED Bulkhead

## Fixture Information

Mounting Method Surface

Fixture Connection Other

IP-rating IP54

Impact Protection (IK) IK04 - 0.50 joule

Colour of the Fixture Black

Housing Aluminium

Emergency Lighting No Emergency Unit

## Sensor Information

Type of sensor Light Sensor

## Why Any-lamp?



Order from the **largest lighting specialist** in Europe



**Customised** quotation



Up to **7 years warranty**



**Easy** return process

